

20V

0030 0050

Charger / Fast Charger

CHARGER LED INDICATION

| LED LIGHT DISPLAY STATUS | SYMBOL | CHARGING STATUS |
|--------------------------|--|---------------------|
| | Green light and red light are blinking | Battery damaged |
| | Blinking green light Constant red light | Fully charged |
| | Constant green light Constant red light | Charging |
| | Blinking red light | Battery over heated |



CG-DX0030
Charger



CG-DX0050
Fast Charger

| Charger Model | Rated output current | Battery Capacity | Charging Time |
|---------------|----------------------|------------------|---------------|
| CG-DX0030 | 4A | 2.0Ah | 40 min |
| | | 4.0Ah | 80 min |
| | | 6.0Ah | 120 min |
| | | 9.0Ah | 180 min |
| CG-DX0050 | 6A | 2.0Ah | 26 min |
| | | 4.0Ah | 48 min |
| | | 6.0Ah | 72 min |
| | | 9.0Ah | 108 min |

The following battery packs can be charged by these chargers

| Battery Model | Rated Battery Capacity (Ah) |
|---------------|-----------------------------|
| BT-DX0030 | 2.0Ah |
| BT-DX0031 | |
| BT-DX0050 | 4.0Ah |
| BT-DX0051 | |
| BT-DX0060 | 6.0Ah |
| BT-DX0061 | |
| BT-DX0090 | 9.0Ah |
| BT-DX0091 | |

Rated voltage: AC 110-240V

Rated frequency: 50/60Hz

Rated input power:

CG-DX0030 : 100W

CG-DX0050 : 150W

Rated output voltage: DC 20V

Protection class:II

Simply Brushless